

HEAT ALARM

MAINS-POWERED | MODEL FIREX KF30R

**INTERLINKED ALARM WITH
RECHARGEABLE SEALED-IN LITHIUM
BACK-UP BATTERY**



Overview & Key Features

Mains-powered heat alarm with rechargeable sealed-in lithium back-up battery that can be interlinked with up to 23 other Kidde mains alarms, be they ionisation, optical or heat. Once interlinked, the detection of the relevant danger by an individual unit will sound across all the connected alarms.

- Interlink with up to 23 Firex hard-wired alarms – all alarms sound if danger is detected
- Alarm memory identifies source unit within interconnecting network
- Combined Test/Hush button allows regular testing of alarm function and can be used to temporarily silence nuisance alarms
- Auto reset after activation
- Tamper-resistant locking device prevents unauthorised removal without the use of a tool
- Mains operation with rechargeable sealed-in lithium back-up battery
- 6-year manufacturer's warranty

Technical Specifications

General

Sensor Type:	Heat
Primary Power Supply:	230V mains-powered with rechargeable sealed-in lithium back-up battery
Sound Output Level	85dB (A) at 3 metres
Mounting Options	Ceiling or wall mounting recommended
Operating Temperature Range:	0°C to 40°C
Humidity Range:	Up to 93% RH (non-condensing)
Storage and Transport:	-20°C to 60°C, 5% to 95% RH (non-condensing)

Technical

Sensor:	Heat
Button Test:	Simulates the effect of heat at the sensor, checks electronics and sounder
Automatic Self-test:	Circuitry is tested and unit beeps (chirps) if fault is detected
Supply Voltage:	230V AC, 50 Hz (nominal UK voltage)
Power Consumption:	< 15mA
Connection:	Push-in/snap-fit type connector with 150mm long flying leads (supplied)
Battery Back-up:	User-replaceable alkaline 9V battery (522/6LR61)
Power-on Indicator:	Continuous green LED
Alarm Sounder:	Electronic piezo-electric sounder (T3 pattern sound: three pulses - space - three pulses), soldered contacts
Sound Output:	85db (A) minimum at 3 metres
Alarm Frequency:	3.2 kHz typical
Dust Protection:	In-built foam gasket in rear of alarm to prevent dust ingress into rear of the alarm

Technical (continued)

Alarm Status:	Red LED flashes approximately once every five minutes = normal operation Red LED flashes once a second = sensing heat (> 58°C) Red LED flashes once every 10 seconds = in hush condition (auto-reset after 15 minutes)
Interconnection:	Up to 24 Firex and Kidde 'Slick' units (smoke, heat and CO) can be hardwired interconnected
Optional Pattresses:	SMK23RU also has integral switchable relay for operating remote devices
Fixing:	Mounting bracket ring supplied with two 'T' slot fitting option 57mm spacing to a maximum of 90mm for standard screw fitting on back boxes Bracket has 50mm diameter center access hole for cabling

Weights and Dimensions

Alarm Dimensions:	127 x 51 mm
Alarm Weight (including battery):	235g
Case Quantity:	6 units

Certifications/Approvals

BS5446 Part 2:2003, CE
Manufactured to ISO9001 Standard



Warranty

6-year manufacturer's warranty

