













PRODUCT NAME: CAVIUS SMART REMOTE PRODUCT NUMBER: CV9001

# **PRODUCT DATA:**

## **DEVICE TYPE:**

Smart remote with emergency light.

## **USAGE:**

Designed to alert with a rapid flashing warning light, vibration and buzzing when alarming and to remote control the Cavius Wireless alarms Family. Torch function to find escape routes at night.

## **INSTALLATION POSITION:**

The body of the remote has a build-in magnet so that the remote can be installed on metal surfaces.

A larger dean also be added to the and of the product so

A lanyard can also be added to the end of the product so the remote can hang from a hook.

# PRODUCT DIMENSIONS:

D: 58 mm x W: 140 mm

## PRODUCT WEIGHT:

Base remote weight: 48 g.

## OPERATION AC/DC:

DC

# **BATTERY TYPE:**

3 x AAA batteries supplied with the Smart Remote.

## LOW BATTERY INDICATION:

A short acoustic beep will sound to notify a low battery voltage.

# INTERLINK FREQUENCY:

868 MHz. max 20mW

#### SIGNALS:

Transmits RF signals to the Cavius Wireless Family at alarm.

# INTERLINK RANGE:

Minimum 100m in open field as a receiver, and within short range to silence an alarm. Range depends on the building materials and will need to be tested in each individual case.

## SOUND:

Audible indicator.

# **PUSH BUTTON:**

The Smart Remote is equipped with 3 switches:

Sliding learn switch to connect to other alarms in the wireless family.

Test/hush button at the end. Torch button on the side.

## WARRANTY:

10 year

# **OPERATING TEMPERATURE:**

+4°C to +38°C

## **OPERATING HUMIDITY:**

Up to 90% RH non-condensing

# STORAGE TEMPERATURE:

-20°C to +60°C

# STORAGE HUMIDITY:

Up to 93% RH non-condensing

# CONTACT

www.cavius.com

# **MANUFACTURER**

Carrier Fire & Security Danmark A/S



